



BUSTER 2000

Ref. No. 17000

www.sigmasport.com

1 BURNTIME

- 2 x click = on / HIGH: 2,30h » 2000lm
- + 1 x click = MID: 5h » 1100lm
- + 1 x click = LOW: 10h » 600lm
- + 1 x click = ECO: 20h » 300lm
- + 1 x click = Flash: 9h
- + 1 x click = Pulse: 11h
- + 1 x click = SOS: 10h
- + 1 x click 5 sec. = off

2 BATTERY STATUS

- > 71%
- 70-31%
- < 30%

3 FLUORESCENT BUTTON

4 START-UP

Click

Wait 3 sec.

2 x Click

ATTENTION

Do not stare at the operating light source.

5 OVERHEATING

> 59 °C (+3 °C -10%)

AUTO-FUNCTION

- 59 °C (100%)
- 60 °C (90%)
- 63 °C (80%)
- 66 °C (70%)
- 69 °C (60%)
- 72 °C (50%)
- 75 °C (5%)

CONTENTS

- BUSTER 2000 (IP44)
- BUSTER 2000 BATTERY PACK (IP44) Ref. No. 17004
- BUSTER 2000 CHARGER (IP20) Ref. No. 17005
- Extension cable
- Remote control (IP44) Ref. No. 17002

SCREW BRACKET

HELMET BRACKET

BUSTER 2000 ADAPTER FOR ACTION CAMERA MOUNT

BATTERY PACK
(Manufacturer: SIGMA-ELEKTRO GmbH)

1 BATTERY STATUS

- 100%
- 75%
- 50%
- 25%
- 1 x Click

2 CHARGING

ca. 5 h

3 USB CHARGING

Output only
USB
Micro USB cable not incl.

1 x Click

Device not included

You have to push the button, once, before charging can start. The charging starts, but without pushing no charging.

4 USB SILICONE PLUG

IP44
Close waterproof

Please always keep the silicone plug closed after charging.

5 INSTALLATION

SIGMA BIKE COMPUTER ATS / STS

> 10 cm

REMOTE CONTROL

1 PAIRING

Disconnect BUSTER 2000

Press for 2 sec

CONNECTING

Click

Connect BUSTER 2000

1 x Click

2 MODI

BUTTON 1

ON/OFF
2 x click = ON
press 5 sec. = OFF

FLASH
+ 1 x click = Flashing
+ 1 x click = Pulse
+ 1 x click = SOS flashing

BUTTON 2

PERMANENT
+ 1 x click = HIGH
+ 1 x click = MID
+ 1 x click = LOW
+ 1 x click = ECO

3 INSTALLATION

4 REMOTE BATTERY INDICATOR

= OK
= 0%

5 BATTERY CHANGE

6 SLEEP MODE

1h INACTIVE

Zzz

Click

The remote control falls in a sleep mode after 1 hour of non-usage. You have to activate the BUSTER 2000 directly on the housing.

7 FLUORESCENT BUTTON

